

Panasonic NCP500/1000 Anonymous Call Telia

Written by Administrator

Tuesday, 10 January 2012 15:30 - Last Updated Tuesday, 10 January 2012 15:54

Incomming call from Telia (Anonumous) will not work.

Problem is the incoming from header, Panasonic don't like this from header and the call will never be set up.

Workaround, you have to use IX78 header manipulation to change the incoming from header, to be able to use header manipulation you need at least a SIP Trunk license and a SIP Trunk installation. Add this string after the phonenumber (Forward to PBX account)

?From=\$(from.dname)%20%3csip%3aanonymous%40\$(from.host)%3e

EX:

08123456789?From=\$(from.dname)%20%3csip%3aanonymous%40\$(from.host)%3e

This will only work in latest firmware to IX78 **5.33F4** or later beta release.

Main Trunk Line									
Reg. Acc.	Used when not defined below	Display Name	User Name	Identity	Authentication		Dyn. Regs.	Inco Trun	
					User ID	Password			
<input checked="" type="checkbox"/>			087062530		0870625	*****	1	087	
(For some services, above Identity, User ID and Password are used for all lines and have not to be entered below)									
PBX Lines (for the enterprise PBX)									
Reg. Acc.	From PBX Number/User	Display Name	User Name	Identity	Authentication		Dyn. Regs.	Inco Trun	
					User ID	Password			
<input checked="" type="checkbox"/>	*87062531		087062531		0870625		1	087	
<input checked="" type="checkbox"/>	*87062532		087062532		0870625		1	087	
<input type="checkbox"/>							0		
<input type="checkbox"/>							0		

SIP Switch functionality is available for PBX Line Accounts with entered extension numbers and then require

Panasonic NCP500/1000 Anonymous Call Telia

Written by Administrator

Tuesday, 10 January 2012 15:30 - Last Updated Tuesday, 10 January 2012 15:54
